

싱글 채널 수신반 GTC-520A



Features

- 상황에 따라 3단 경보 농도를 LED에 표시합니다.
- 벽걸이형으로 설계되어 설치가 용이합니다.
- RS-485 Modbus 통신이 가능합니다.
- 자가진단 기능이 내장되어 있습니다.
- Relay 접점 출력 기능을 제공합니다.
- 경보 관련 농도 및 지연 시간 등을 임의 설정할 수 있습니다.

Accessories



RS-485 Module

제품 사양

Operation display	6-LED (Power, 3-Stage alarm, Trouble, Stand-by)
Measuring display	0.315" 4-Digit, Bar-Graph (32 Segment, 3-Color LED)
Measuring range	1~9999 (Programmable) / % LEL, ppm, % vol
Alarm display	Visual : 3-Stage alarm, Trouble LED, Warning light audible : Buzzer
Alarm output signal	3-Stage alarm, Trouble/ AC250V 3A relay contact (SPDT)
Alarm level set	Programmable with in detection range
Input signal	4~20mA DC (2-Wire or 3-Wire)
Output signal	4~20mA DC Isolated RS-485 Communication Modbus (Option)
Reset signal	Reset switch and remote control
Program set mode	Alarm value (1,2,3 Alarm)
	Alarm time (Instant & Delay) 1~30min Alarm dead band Measuring value offset (SAD)
Operating temperature	-20°C ~ 60°C
Operating humidity	5~99% RH (Non-condensing)
Dimension	135(W) x 210(H) x 81(D) mm
Weight	508g

제품 인증

기타 인증	CE(EMC)	국내 전자파 인증	-
-------	---------	-----------	---