

싱글 채널 수신반 (Backup Battery 탑재)

GTC-552



Features

- 3-Digit로 가스 농도를 표시합니다.
- 상황에 따라 3단 경보 농도를 LED에 표시합니다.
- 백업 배터리(24V600mA)가 장착되어 있습니다.
- 벽걸이형으로 설계되어 설치가 용이합니다.
- RS-485 Modbus 통신이 가능합니다.
- 자가진단 기능이 내장되어 있습니다.
- 경광등과 결합 가능합니다.

Accessories



RS-485 Module

제품 사양

Operation display	10-LED (Main power, Batt power, Batt status, Batt trouble, 3-Stage alarm, Trouble, Stand-by, Status for communicate)
Measuring display	3.0" 3-Digit
Measuring range	1~999 (Programmable) / % LEL, ppm, % vol
Alarm display	Visual : 3-Stage alarm, Trouble LED, Warning light audible : Buzzer
Alarm output signal	3-Stage alarm, Trouble / AC250V 3A relay contact (SPDT)
Alarm level set	Programmable with in detection range
Input signal	4~20mA DC (2-Wire or 3-Wire)
Output signal	4~20mA DC Isolated RS-485 Communication Modbus (Option)
Reset signal	Reset switch and remote control
Program set mode	Alarm value (1,2,3 Alarm)
	Alarm time (Instant & Delay) 1~30min Alarm dead band Measuring value offset (SAD) Relay output on/off
Operating temperature	-20°C ~ 60°C
Operating humidity	5~99% RH (Non-condensing)
Dimension	280(W) x 389(H) x 153(D) mm
Weight	2.7kg
Backup battery	24V / 600mAh, Ni-Cd Battery